

DHI-ART-ARC3800H-06-FW2

Dahua Wireless Alarm KIT













System Overview

The Alarm Kit contains all the products required for a basic wireless alarm system, providing you and your assets with strong protection.

Technical Specification				
Port				
Wireless Zone	Hub:150 channels wireless peripherals (6 sirens, 64 PIR cameras (only 8 indoor PIR cameras), 64 keyfobs, 8 keypads and 4 repeaters)			
Network Mode	Hub: Ethernet, Wi-Fi and Cellular network (Supports installation of dual SIM cards. Only one card can be enabled at a time)			
Network Port	Hub: $1 \times RJ-45$, $10/100$ Mbps Ethernet port.			
Storage Battery	Hub: One built-in 4,750 mAh rechargeable lithium battery.			
Video & Audio				
Video Input	Hub: 8-ch IPC, which only supports the upload of alarm videos.			
Audio Output	Hub: 1 channel			
Volume Control	Hub: Yes			
Voice Broadcast	Hub: Telephone and local speaker			
Function				
Indicator Light	Hub: The indicator indicates the status of alarms, arming and disarming, the network connection and device failure. Keyfob: 1 dual-color status indicator (Green means normal and red means abnormal) PIR Detector: 1 green alarm indicator Siren: 1 green alarm indicator External Siren: 1 green alarm indicator, 12 alarm LED groups			
Button	Hub: Includes a reset button, voltage button and AP switch button. Keyfob: 4 (Home, Away, Disarm, and SOS) PIR Detector: 1 power switch Siren: 1 power switch			

External Siren: 1 power switch

- \cdot Supports alarm video verification through integration of the IPC with the hub
- \cdot Images can be remotely and quickly transferred from the PIR-Cam to the device.
- · Features voice call alarm.
- · Supports wired and AP network configuration methods, which makes it easier to add the hub to apps and to switch to the hub's network.
- · Supports multi-network redundancy for Ethernet, Wi-Fi and 4G net works to ensure the network remains stable and reliable.
- · Supports two-way communication and frequency hopping to make communication with wireless peripherals stable and reliable. Features cloud update
- \cdot You can also remotely update the device and wireless peripherals on the mobile app.
- \cdot Offers a dual backup system, and uses auto recovery when an update fails.

Phone Call Hub: Yes (up to 5 phone numbers) Video Linkage Hub: Yes Offline Cache Hub: Stores up to 50 alarm messages. Arm and Disarm Hub: App, Keypad, remote control, card, scheduled arming and disarming. Remote Update All: Cloud update Low Battery Detection All: Yes Tamper Hub: 33 app users (31 general users, 1 admin user and 1 installer) and 32 keypad users Power Failure Protection for Configured Parameters Logs Hub: Up to 5, 000 entries Measuring Range (Temperature) PIR Detector: -15 °C to +65 °C (+5 °F to +149 °F) (indoor) Siren: -15 °C to +65 °C (+5 °F to +149 °F) (indoor) Transmission Protocol Hub: SIA, SoftGuard Technical Sensor PIR Detector: Dual elements low-noise PIR sensor Detection Mode PIR Detector: 3 levels adjustable PIR Detector: 12 m (39.37 ft) (90°) with installation height of 2.2 m (7.21 ft)			
Video Linkage Offline Cache Hub: Stores up to 50 alarm messages. Arm and Disarm Remote Update Low Battery Detection All: Cloud update Low Battery Detection All: Yes Tamper Hub: Yes PIR Detector: Yes Siren: Yes User Management Hub: 33 app users (31 general users, 1 admin user and 1 installer) and 32 keypad users Power Failure Protection for Configured Parameters Logs Hub: Up to 5, 000 entries Measuring Range (Temperature) PIR Detector: -15 °C to +65 °C (+5 °F to +149 °F) (indoor) Transmission Protocol Hub: SIA, SoftGuard Technical Sensor PIR Detector: Dual elements low-noise PIR sensor Detection Mode PIR Detector: 3 levels adjustable PIR Detector: 12 m (39.37 ft) (90°) with installation	SMS	Hub: Yes (up to 5 phone numbers)	
Offline Cache Hub: Stores up to 50 alarm messages. Arm and Disarm Hub: App, Keypad, remote control, card, scheduled arming and disarming. Remote Update All: Cloud update Low Battery Detection All: Yes Tamper Hub: Yes PIR Detector: Yes Siren: Yes User Management Hub: 33 app users (31 general users, 1 admin user and 1 installer) and 32 keypad users Power Failure Protection for Configured Parameters Hub: Yes Hub: Up to 5, 000 entries Measuring Range (Temperature) PIR Detector: -15 °C to +65 °C (+5 °F to +149 °F) (indoor) Transmission Protocol Hub: SIA, SoftGuard Technical Sensor PIR Detector: Dual elements low-noise PIR sensor Detection Mode PIR Detector: 3 levels adjustable PIR Detector: 12 m (39.37 ft) (90°) with installation	Phone Call	Hub: Yes (up to 5 phone numbers)	
Arm and Disarm Remote Update All: Cloud update Low Battery Detection All: Yes Hub: Yes PIR Detector: Yes Siren: Yes User Management Hub: Yes Power Failure Protection for Configured Parameters Logs Hub: Up to 5, 000 entries Measuring Range (Temperature) Transmission Protocol Hub: SIA, SoftGuard Technical Sensor PIR Detector: Dual elements low-noise PIR sensor Detection Mode PIR Detector: 3 levels adjustable PIR Detector: 12 m (39.37 ft) (90°) with installation	Video Linkage	Hub: Yes	
Arm and Disarm arming and disarming. Remote Update All: Cloud update Low Battery Detection All: Yes Hub: Yes PIR Detector: Yes Siren: Yes User Management Hub: 33 app users (31 general users, 1 admin user and 1 installer) and 32 keypad users Power Failure Protection for Configured Parameters Logs Hub: Up to 5, 000 entries Measuring Range (Temperature) PIR Detector: -15 °C to +65 °C (+5°F to +149 °F) (indoor) Transmission Protocol Hub: SIA, SoftGuard Technical Sensor PIR Detector: Dual elements low-noise PIR sensor Detection Mode PIR Detector: 3 levels adjustable PIR Detector: 12 m (39.37 ft) (90°) with installation	Offline Cache	Hub: Stores up to 50 alarm messages.	
Low Battery Detection All: Yes Hub: Yes PIR Detector: Yes Siren: Yes User Management Hub: 33 app users (31 general users, 1 admin user and 1 installer) and 32 keypad users Power Failure Protection for Configured Parameters Logs Hub: Up to 5, 000 entries Measuring Range (Temperature) PIR Detector: -15 °C to +65 °C (+5°F to +149 °F) (indoor) Siren: -15 °C to +65 °C (+5°F to +149 °F) (indoor) Transmission Protocol Hub: SIA, SoftGuard Technical Sensor PIR Detector: Dual elements low-noise PIR sensor Detection Mode PIR Detector: 3 levels adjustable Petertion Pange PIR Detector: 12 m (39.37 ft) (90°) with installation	Arm and Disarm		
Tamper Hub: Yes PIR Detector: Yes Siren: Yes User Management Hub: 33 app users (31 general users, 1 admin user and 1 installer) and 32 keypad users Power Failure Protection for Configured Parameters Hub: Yes Logs Hub: Up to 5, 000 entries Measuring Range (Temperature) PIR Detector: -15 °C to +65 °C (+5°F to +149 °F) (indoor) Siren: -15 °C to +65 °C (+5°F to +149 °F) (indoor) Transmission Protocol Hub: SIA, SoftGuard Technical Sensor PIR Detector: Dual elements low-noise PIR sensor Detection Mode PIR Detector: 3 levels adjustable Petertion Pange	Remote Update	All: Cloud update	
Tamper PIR Detector: Yes Siren: Yes Hub: 33 app users (31 general users, 1 admin user and 1 installer) and 32 keypad users Power Failure Protection for Configured Parameters Logs Hub: Yes Hub: Up to 5, 000 entries Measuring Range (Temperature) PIR Detector: -15 °C to +65 °C (+5°F to +149 °F) (indoor) Siren: -15 °C to +65 °C (+5°F to +149 °F) (indoor) Transmission Protocol Hub: SIA, SoftGuard Technical Sensor PIR Detector: Dual elements low-noise PIR sensor Detection Mode PIR Detector: 3 levels adjustable Petertion Pange	Low Battery Detection	All: Yes	
User Management and 1 installer) and 32 keypad users Power Failure Protection for Configured Parameters Hub: Yes Logs Hub: Up to 5, 000 entries Measuring Range (Temperature) PIR Detector: -15 °C to +65 °C (+5°F to +149 °F) (indoor) Siren: -15 °C to +65 °C (+5°F to +149 °F) (indoor) Transmission Protocol Hub: SIA, SoftGuard Technical Sensor PIR Detector: Dual elements low-noise PIR sensor Detection Mode PIR Detector: 3 levels adjustable Petertion Pange PIR Detector: 12 m (39.37 ft) (90°) with installation	Tamper	PIR Detector: Yes	
Configured Parameters Logs Hub: Up to 5, 000 entries Measuring Range (Temperature) PIR Detector: -15 °C to +65 °C (+5°F to +149 °F) (indoor) Siren: -15 °C to +65 °C (+5°F to +149 °F) (indoor) Transmission Protocol Hub: SIA, SoftGuard Technical Sensor PIR Detector: Dual elements low-noise PIR sensor Detection Mode PIR Detector: 3 levels adjustable Petertion Pange PIR Detector: 12 m (39.37 ft) (90°) with installation	User Management	and 1 installer) and	
Measuring Range (Temperature) PIR Detector: -15 °C to +65 °C (+5°F to +149 °F) (indoor) Siren: -15 °C to +65 °C (+5°F to +149 °F) (indoor) Transmission Protocol Hub: SIA, SoftGuard Technical Sensor PIR Detector: Dual elements low-noise PIR sensor Detection Mode PIR Detector: PIR Sensitivity PIR Detector: 3 levels adjustable PIR Detector: 12 m (39.37 ft) (90°) with installation		Hub: Yes	
Measuring Range (Temperature) (indoor) Siren: -15 °C to +65 °C (+5 °F to +149 °F) (indoor) Transmission Protocol Hub: SIA, SoftGuard Technical Sensor PIR Detector: Dual elements low-noise PIR sensor Detection Mode PIR Detector: 9 IR Sensitivity PIR Detector: 3 levels adjustable Petertion Pages PIR Detector: 12 m (39.37 ft) (90°) with installation	Logs	Hub: Up to 5, 000 entries	
Technical Sensor PIR Detector: Dual elements low-noise PIR sensor Detection Mode PIR Detector: PIR Sensitivity PIR Detector: 3 levels adjustable Petection Pance PIR Detector: 12 m (39.37 ft) (90°) with installation	9 9	(indoor)	
Sensor PIR Detector: Dual elements low-noise PIR sensor Detection Mode PIR Detector: PIR Sensitivity PIR Detector: 3 levels adjustable PIR Detector: 12 m (39.37 ft) (90°) with installation	Transmission Protocol	Hub: SIA, SoftGuard	
Detection Mode PIR Detector: PIR Sensitivity PIR Detector: 3 levels adjustable PIR Detector: 12 m (39.37 ft) (90°) with installation	Technical		
Sensitivity PIR Detector: 3 levels adjustable PIR Detector: 12 m (39.37 ft) (90°) with installation	Sensor	PIR Detector: Dual elements low-noise PIR sensor	
PIR Detector: 12 m (39.37 ft) (90°) with installation	Detection Mode	PIR Detector: PIR	
	Sensitivity	PIR Detector: 3 levels adjustable	
	Detection Range		

Detection Speed	PIR Detector: 0.3 m/s–3 m/s (0.98 ft/s–9.84 ft/s)	Net Weight	Hub: 510 g (1.12 lb) Keyfob: 20 g (0.04 lb)
Pet Immunity Level	PIR Detector: ≤18 kg (39.68 lb)		PIR Detector: 100 g (0.22 lb) External Siren: 610 g (1.34 lb)
White Light Resistance Level	PIR Detector: 6500 lx	6 W. L.	Siren: 105 g (0.23 lb)
Two-way Digital Temperature Compensation	PIR Detector: Yes, no attenuation of detection distance in high temperature.	Gross Weight	Kit: 3 kg (6.61 lb)
Sound Pressure	Siren: ≥105 ± 3 dB\1M External Siren: 95.2 ≤ LAFmax [dB(A)] ≤ 104.9 (EN 50131-4:2019)	Installation	Hub: Wall mount; Desktop mount PIR Detector: Wall mount External Siren: Wall mount Siren: Bracket mount
Wireless		Casing Material	All: PC + ABS
Carrier Frequency	All: 433.1 MHz-434.6 MHz	Protection	External Siren: IP65
Transmitter Power (EIRP)	All: Limit 10 mW	Certifications	All: CE,RCM
Communication Mechanism	All: Two-way	Anti-corrosion Level	Basic Protection
Communication Distance	Hub: Up to 1,400 m (4,593.18 ft) in an open space. Keyfob: Up to 500 m (1,640.42 ft) in an open space. PIR Detector: Up to 1,200 m (3937.01 ft) in an open space. Siren: Up to 800 m (2,624.67 ft) in an open space External Siren: Up to 1,200 m (3,937.01 ft) in an open space	Storage Temperature	Hub: -10 °C to +50 °C (+14 °F to +122 °F) (indoor) Keyfob: -10 °C to +55 °C (+14 °F to +131 °F) (indoor) PIR Detector: -10 °C to +55 °C (+14 °F to +131 °F) (indoor) External Siren: -25 °C to +60 °C (-13 °F to +140 °F) Siren: -10 °C to +55 °C (+14 °F to +131 °F) (indoor)
Encryption Mode	All: AES128	Storage Humidity	All: 10%-90% (RH)
Frequency Hopping	All: Yes	Packaging Dimensions	Kit: 288 mm \times 256 mm \times 237 mm (11.34" \times 10.08" \times 9.33") (L \times W \times H)
General		Wi-Fi	
Language	English	W: F: Chandard	High JEEF 2002 11h /a /a
Hub: 100-240 VAC, 50/60 HZ Keyfob: CR2032 battery Power Supply PIR Detector: CR123A battery	Wi-Fi Standard Wi-Fi Frequency Range	Hub:1EEE 802.11b/g/n Hub:2400-2483.5 MHz	
Siren: 2 CR123A batteries External Siren: 4 CR123A batteries/9-15 VDC		Wi-Fi Power Transmission	Hub:≤20 dBm@2400-2483.5 MHz
char conr alarn Standby Time 1,80	Hub: The battery lasts up to 12 hours when it is fully charged and is within the following conditions: It is connected to the Wi-Fi, its ID is connected to the alarm receiving center, the heartbeat interval is 1,800 seconds, and it is connected to 8 peripherals and the cloud.	Cellular Network	
		Cellular Network Standard	Hub:GSM/WCDMA/LTE
	Keyfob: 3 years PIR Detector: 4 years Hub: Max 12 W	Frequency Range	Hub: EU and AU: 4G: FDD-LTE: B1/B3/B7/B8/B20/ B28A; TDD-LTE: B38/B40/B41; 3G: WCDMA: B1/B8; 2G: GSM: 1,800/900 MHz
Power Consumption	Keyfob: Max 100 mW PIR Detector: Max 120 mW		Hub: EU: 4G: Power class3: 23 dBm ± 2 dB 3G: Power class3: 24 dBm+1/-3 dB 2G: Power class0: 30 dBm ± 3 dB (GSM900) Power class5: 33 dBm ± 3 dB (GSM1800)
	VDC)		
Operating Temperature	Hub: -10 °C to +55 °C (+14 °F to +131 °F) (indoor) Keyfob: -10 °C to +55 °C (+14 °F to +131 °F) (indoor) PIR Detector: -10 °C to +55 °C (+14 °F to +131 °F) (indoor) Siren: -10 °C to +55 °C (+14 °F to +131 °F) (indoor) External Siren: -25 °C to +60 °C (-13 °F to +140 °F)		
Operating Humidity	All: 10%–90% (RH)		
Product Dimensions	Hub: $174.8 \text{ mm} \times 174.8 \text{ mm} \times 38.3 \text{ mm} (6.88" \times 6.88" \times 1.51") (L \times W \times H)$ Keyfob: $60.0 \text{ mm} \times 39.5 \text{ mm} \times 15.0 \text{ mm} (2.36" \times 1.56" \times 0.59") (L \times W \times H)$ PIR Detector: $104.0 \text{ mm} \times 60.0 \text{ mm} \times 50.0 \text{ mm} (4.09" \times 2.36" \times 1.97") (L \times W \times H)$ Siren: $81.0 \text{ mm} \times 81.0 \text{ mm} \times 26.0 \text{ mm} (3.19" \times 3.19" \times 1.02") (L \times W \times H)$ External Siren: $200 \text{ mm} \times 200 \text{ mm} \times 52.5 \text{ mm} (7.87" \times 7.87" \times 2.07") (L \times W \times H)$		
	, ,		

Ordering Information

Type Model Description

Alarm KIT DHI-ART-ARC3800H- 1*Hub ARC3800H-FW2 1*Keyfob ARA24-W2

3*PIR Detector ARD1233-W2 1*Internal Siren ARA12-W2 1*External Siren ARA13-W2

Application

